

## PAM-60/120 Mixer/Amplifier



- Output Power : PAM-60 : 60W(RMS) < 1% THD  
PAM-120 : 120W(RMS) < 1% THD
- Inputs : 6 Balanced with adjustable sensitivity
- Option : XLR, 1/4", RCA, screw terminal, tuner, CD player, cassette  
Telephone Input : Screw terminal
- 2 Band Equalizer :  $\pm 12$ dB
- Priority Muting : Ch1, 2, chime, telephone input adjustable
- Remote Control : 4 Tone chime for announcement
- Line in/out for additional mixer or amp link
- 5 Individual speaker zone selector and all call
- Power Source : 100-120VAC or 220-240VAC; 50/60Hz, DC 24V  
(supplied AC mains transformer depends on country requirements)
- Power Consumption : PAM-60 : 150W, PAM-120 : 300W
- Weight : PAM-60 : 11.4kg / 25.1lb, PAM-120 : 13.5kg / 29.7lb
- Dimensions : 420(W)X132(H)X360(D)mm / 16.5(W)X5.2(H)X14.1(D)in

## PAM-240/360 Mixer/Amplifier



- Output Power : PAM-240 : 240W(RMS) < 1% THD  
PAM-360 : 360W(RMS) < 1% THD
- Inputs : 6 Balanced with adjustable sensitivity  
Option : XLR, 1/4", RCA, screw terminal, tuner,  
CD player, cassette  
Telephone Input : Screw terminal
- 3 Band Equalizer :  $\pm 12$ dB
- Priority Muting : Ch1, 2, chime, telephone input adjustable
- Remote Chime : 4 Tone chime for announcement
- Remote speaker control used for external remote amplifier
- Line in/out for additional mixer or amp link
- 5 Individual speaker zone selector and all call
- Power Source : 100-120VAC or 220-240VAC; 50/60Hz  
(supplied AC mains transformer depends on country requirements)
- Power Consumption :  
PAM-240(230V-240V) : 240W, (100V-120V) : 250W  
PAM-360(230V-240V) : 300W, (100V-120V) : 380W
- Weight : PAM-240 : 11kg / 24.2lb, PAM-360 : 13kg / 5.1lb
- Dimensions : 420(W)X132(H)X360(D)mm / 16.5(W)X5.2(H)X14.1(D)in

## RM-05 Remote Microphone Station



- Speaker zones of PAM-240/360 can be controlled by RM-05
- Zone control switches
- Dynamic gooseneck microphone
- Pre-announcement chime
- LED output level indication
- Power Source : DC 24V(DIN connector)
- Weight : 900g / 2lb(without Microphone)
- Dimensions : 194(W)X60(H)X205(D)mm / 7.6(W)X2.3(H)X8(D)in

## PAM-T Tuner for PAM-Series Mixer/Amplifiers



- PAM series digital tuner module with 30 programmable presets
- Music on hold signal

## PAM-D Cassette Deck for PAM-Series Mixer/Amplifiers



- PAM series cassette module
- Front loading auto reverse cassette deck

## PAM-CDA CD Player for PAM-Series Mixer/Amplifiers



- PAM series CD module
- Function : Random play, music scan, time counter, repeat,  
forward, reverse track, forward, music search